

EQUALIZER

TECHNICAL FIELD

The present invention refers to a method to equalize signals transmitted on a line as well as an equalizer filter realized in CMOS technology and besides an integrated
5 circuit comprising an equalizer circuit.

BACKGROUND OF THE INVENTION

In high speed line communications, for instance in the case of data transmission of SDH equipment, the only filtration of the received signal is not sufficient to recover the data with a small error rate. An equalizer circuit is therefore necessary to
10 compensate the line loss and improve the intersymbol interferences of the datum to recover. As known the line dispersion losses are linearly proportional to the length of the line and besides they are proportional to the square root of the frequency of transmission. The equalizer must therefore have a frequency response inversely proportional to that of the line. Particularly it is necessary an adaptive equalizer able to deal with variable lengths of
15 line without altering significantly the intersymbol interferences.

SUMMARY OF THE INVENTION

An embodiment of the present invention realizes an equalizer able to compensate the line attenuations in a simple and effective way.

Another embodiment of the invention is directed to a method that equalizes
20 signals transmitted on a line comprising the following phases: applying an analogical adaptive filter in series with said line, having a working frequency band and having at least one pole and at least one zero the position of which in said working frequency band is variable in response to the attenuation of said line; applying a retroaction circuit to the output of said filter able to vary the position of said at least one pole and at least one zero;
25 setting said at least one pole and at least one zero in correspondence to a prefixed frequency of said working frequency band; moving the position of said at least one pole

toward the high frequencies at the increasing of said attenuation of said line; and moving the position of said at least one zero toward the low frequencies at the increasing of said attenuation of said line.

An equalizer circuit according to an embodiment of the present invention

5 equalizes signals transmitted on a line having an attenuation comprising: an analogical adaptive filter applied in series to said line comprising plural transconductance filters having a bias current each and to which it is associated at least one pole and at least one zero the position in frequency of which in the working band is variable in response to said bias current; a retroaction circuit applied to the output of said filter able to vary said bias

10 current; said bias current varies at the varying of said attenuation of said line; wherein said transconductance filters have said bias current of prefixed value; said bias current is made to vary at the increasing of said attenuation so that said at least one pole is moved toward the high frequencies; and said bias current is made to vary at the increasing of said attenuation so that said at least a zero is moved toward the low frequencies. The equalizer

15 circuit can be an integrated circuit of CMOS type

Thanks to the present invention it is possible to realize a linear equalizer that does not require of any external regulation. It results to be very simple as the retroaction loop checks only the output voltage. Besides realizing it completely in CMOS technology it is possible to integrate it with other circuits on a single chip.

20 BRIEF DESCRIPTION OF THE DRAWINGS

The characteristics and the advantages of the present invention will result evident from the following detailed description of one of its embodiment, illustrated as example not limitative in the joined sketches, in which:

the Figure 1 shows a blocks scheme of an equalizer according to the present

25 invention;

the Figure 2A shows a schematic circuit of an example of a transconductance filter and the Figure 2B its Bode diagram;

the Figure 3 shows a schematic circuit of an example of a circuit 4 that provides an indication of the variation of the line attenuation;

the Figure 4 shows a schematic circuit of an example of the circuit of charge pump 5;

5 the Figure 5 shows a schematic circuit of an example of a variable bias generator 7;

the Figure 6 shows a diagram that shows the course of the voltage to the terminal of the capacitor 6 and the course of the control current of the adaptive filter 1;

10 the Figure 7 shows a diagram that shows the positioning and the variations of the poles/zeros in the frequencies plane;

the Figure 8 shows a diagram that shows the course of the transfer function of the filter 1 in the frequency at the varying of the line attenuation; and

the Figure 9 shows a schematic circuit of a bias generator 8 dependent on the process.

15 DETAILED DESCRIPTION OF THE INVENTION

A block scheme of an equalizer according to an embodiment of the present invention, shown in Figure 1, comprises an input signal 10, coming from a line, applied to an adaptive filter 1 which provides an output 11. The signal at the output of the adaptive filter 1 is applied to a comparator 3 that compares this signal 11 with a reference voltage 13. At the output of the comparator 3 there is a filter 14 composed of a first circuit 4 that provides an indication of the variation of the line attenuation, connected to a charge pump 5 which in turn is connected to a capacitor 6. The circuit 4 is sampled by a working frequency 15. The voltage at the terminals of the capacitor 6 is applied to a variable bias generator 7. To the generator 7 are applied, preferably, also the signals Pr1-Prm coming from a bias generator 8 dependent on the process. The signals Pc1-Pcn in output from the generator 7 are applied to the adaptive filter 1.

The filter 1 comprises preferably adaptive filters of the transconductance type with biquadratic cells, for instance in Figure 2A is drawn the block scheme of a

transconductance filter having one pole which has an input 20 and it comprises a first stage 21 having transconductance G_m , and a second stage 22 having transconductance G_{mD} , an output 23. Between the first stage 21 and the second stage is connected a capacitor C . To the first stage 21 is connected a terminal P_{c1} and to the second stage 22 is connected a terminal P_{c2} , which receives the bias current. The bias current P_{c2} varies the G_{mD} transconductance of the circuit which varies the position of the pole in frequency in the working band accordingly. In fact it could be seen from the Figure 2B, where it is represented the Bode diagram of the circuit of Figure 2A, that the position of the pole in frequency is given by the division G_{mD}/C and the point in which the gain module is equal to 1 it is equal to G_m/C . Therefore making the bias current P_{c2} to vary, varies the value of G_{mD} and therefore the pole frequency position. The bias current P_{c1} makes vary the G_m transconductance of the circuit which, if it is made to vary in a separate way as regards the current P_{c2} , it makes vary the continuous gain accordingly, which as it could be seen in the Figure 2B it is equal to G_m/G_{mD} . If the bias current P_{c1} and P_{c2} have been made to vary of the same quantity the pole position moves but the continuous gain does not vary.

To each filter of this type could be associated either one pole or one zero in accordance to the particular type of circuit. To be able to vary the position of each pole and of each zero it is necessary a bias current for each of them and a current to make vary (increase) the continuous gain of a prefixed value. In an example of realization of the present invention, the filter 1 comprises two biquadratic filters and one at a single stage, for a total of 5 poles and of 5 zeros. Such types of filters are well known by the skilled in the art, and they are not furtherly described, an example of such filters could be found in the article of F. Rezzi, I. Bietti, M. Cazzaniga and R. Castello by the title "A 70 mW seventh order filter with 7-50 MHz cut-off frequency and programmable boost and group delay equalization" published in the IEEE Journal of solid state circuits, vol. 32, No. 12, December 1997.

The signals P_{c1} - P_{cn} correspond to the bias current (variable at the varying of the line attenuation) of the transconductance filters; preferably these bias currents are

compensated by the Pr1-Prm signals that correspond to the currents supplied by the bias generator 8 which depend on the thermal and constructive variations of the device.

A schematic circuit of an example of the line attenuator detector 4 that supplies an indication of the variation of the line attenuation, shown in Figure 3, comprises a first bistable circuit 31 of D type and a second bistable circuit 32 of D type. The output of the comparator 3 is applied to a terminal 35 of the first bistable circuit 31 which corresponds to the reset input R of the circuit and also to an input of a NOR circuit 33, the output Q of which is connected to the input D of the bistable 31. The output Q of the bistable 31 is applied the input D of the second bistable circuit 32, the output Q of which is applied to the output terminal 36. The output Q of the bistable 31 is also applied to the second input of the NOR circuit 33. A clock signal is applied to the terminal 15 that it is connected to the clock input of the bistable 32 and it is also connected to the clock input of the bistable 31 through an inverter circuit 34.

A schematic circuit of an example of the charge pump circuit 5, shown in Figure 4, comprises a first transistor 41 with p channel and a second transistor 42 with n channel having the gates connected together in order to form an input terminal 36 (connected to the output of the circuit 4), the source of the transistor 41 is connected to the supply voltage, the transistor source 42 is connected to ground, the drain of the transistor 42 is connected to the drain of the transistor 41 and they are connected to a terminal 44 of the capacitor 6, the other terminal of the capacitor 6 is set to ground. If the input signal 36 of the charge pump circuit 5 is at high level, the capacitor 6 discharges itself, if the signal is at a low level the capacitor 6 charges itself.

The whole of the circuits 4, 5 and 6 constitute the filter 14 that integrates the signal in output from the comparator 3 and it provides in output a signal proportional to the course of the line attenuation that is used to predispose the bias and control current Pc1-Pcn of the filter 1.

Particularly the circuit 4, drawn in Figure 3 provides in output a signal for instance of high level if the signal in output from the comparator 3 is remained high for at least one clock cycle of the working frequency 15. Varying the working frequency 15 it is

possible to vary the reaction times of the circuit at the varying of the line attenuation. The charge pump 5, charges and discharges the capacitor 6 so that to its terminals it is present a voltage proportional to the value of line attenuation opportunely filtered.

A schematic circuit of an example of a variable bias generator 7, shown in Figure 5, comprises a terminal 44 to which it has been applied the voltage present on the capacitor 6, connected to the gate of a transistor 45 with n channel, the source is connected to ground and the drain is connected to a branch of a first current mirror 46 which is connected to the supply voltage V_{cc} through a transistor 47 with p channel. The other branch of the current mirror 46 is connected to a branch of a second current mirror 48, and in the other branch of the second current mirror 48 flows a current I_{c1} and corresponds to the terminal Pc1. The drain of the transistor 45 is connected also to the source of the transistor 49 with n channel. The drain of the transistor 49 is connected to a branch of a third current mirror 50 which is connected directly to the supply voltage V_{cc} . The other branch of the third current mirror 50 is connected to a branch of a fourth current mirror 51, and in the other branch of the fourth current mirror 51 flows a current I_{c2} and corresponds to the terminal Pc2. The gate of the transistor 49 is connected to the drain of a transistor 53 having the source connected to ground and the gate applied the terminal Pr1. The gate of the transistor 49 is also connected to the transistor 52 with p channel connected like a diode and applied to the supply voltage V_{cc} that forms a current mirror together with the transistor 47 the two gates of which are connected together.

In Figure 5, only for representation simplicity have been drawn only the circuits that provide current to the two terminals Pc1 and Pc2 of the filter 1 depending on the value of the input V_c of the capacitor 6 and of the input Pr1 coming from the bias generator 8. Also in this case it has been considered for representation simplicity only one terminal of the plurality of the terminals Pr1-Prn.

The variable bias generator 7 must provide the bias currents by the terminals Pc1-Pcn to the various transconductance filters present in the filter 1. Such bias currents must be placed at quiescent ($V_c = 0$), for instance placed for a line having length equal to 0 and they therefore must vary at the varying of the line attenuation. The generator 7

receives in input the V_c signal from the capacitor 6 and it is able to absorb the current I_{c1} (from the terminal P_{c1}), which starting from V_c equal to null, linearly increases at the increasing of V_c , up to reach a limit of current equal to $I_p/2$, where I_p is the flowing current in the transistor 53, after that it begins to increase linearly the current I_{c2} , (up to a possible circuital limit). The current I_p could be generated by a fixed generator I_p but, the equalizer circuit comprises besides preferably the bias generator 8 which provides a bias current able to compensate the thermal and constructive variations of the equalizer. For instance at the increasing of the temperature the current I_p increases according to the variation of the bias present on the terminal P_{r1} .

In Figure 6 could be seen the waveforms of some signals of the circuit of Figure 5. Particularly it is possible to see the exponential relationship between the input voltage V_c applied to the terminal 44 of the transistor 45 and its relative drain current I_c . Moreover it is possible to see the course of the current I_{c1} and I_{c2} flowing respectively in the mirrors 48 and 51 and correspondent to the bias and control current present on the terminals P_{c1} and P_{c2} .

As already said it has been represented for simplicity a reduced circuit able to provide only two currents to the terminals P_{c1} and P_{c2} . It is however to imagine a series of currents one for each pole and one for each zero present in the filter 1 and besides the current or preferably the currents necessary to increase the continuous gain. The currents relative to each couple of poles/ zeros, positioned in frequency in the same place, will have a similar course as, better explained further on, they will have to move simultaneously, after that the couple of poles/zeros placed immediately at a smaller frequency will move.

The Figure 7 shows a diagram that shows the positioning of the poles/zeros in the frequencies plane, particularly it is possible to note the uniform spacing between the couples of poles/zeros along a logarithmic frequency axle inside the band B of the working frequencies of the filter. Besides it is possible to note the displacement direction that the poles and the zeros effect at the varying (at the increasing) of the line attenuation, in response of the variations of the bias current to the terminals P_{c1} - P_{cn} . Particularly the poles move toward the high frequency and the zeros move toward the low frequency.

Besides the couples of poles/zeros move in succession (in the indicated direction) beginning from the identifying number 71 up to the number 75, finally it is increased the filter continuous gain making the opportune bias currents vary. In practice first moves the pole and the zero of the couple 71 placed at high frequency inside the working band, therefore in succession moves the pole and the zero of the couple 72 placed to a lower frequency as regards the couple 71 that has been moved previously up to the movement of the couple 75 placed at a lower frequency. Therefore, when all the couples have moved it is increased the continuous gain. All the displacement above reported are effected in consequence of the variations of the bias and control current present on the terminals Pc1-
Pcn.

In Figure 8 is shown a diagram of the transfer function of the filter 1 in function of the frequency at the varying of the line attenuation, the arrow points out as varies the transfer function at the increasing of the line attenuation. At the moving of the couples of poles/zeros above mentioned it is possible to see in Figure 8 the variation of the transfer function and particularly it is possible to see that only at the end the continuous gain is varied.

A schematic circuit of an example of a bias generator 8 dependent from the process, shown in Figure 9, comprises a plurality of transistors 61 and 62 with n channel having the source connected to ground, the drains respectively connected to the terminals Pr1-Prm, and the gate connected together and connected to a node at which terminals are connected a gate of a transistor 63, a terminal of a generator of current Iref 67 and a branch of a first current mirror 68. The source of the transistor 63 is connected to ground and the drain is connected to the source of a differential couple formed by the transistors 64 and 65 with channel n which gates are respectively connected to two reference voltages Vref1 and Vref2, with $V_{ref2} > V_{ref1}$, and the drains are connected to a second current mirror 66 connected to the power supply Vcc. The drain of the transistor 64 is also connected to a branch of the mirror 68. This circuit generates currents able to compensate the variations in temperature, of the supply voltage and of the dispersions of the characteristics (from device to device) due to the construction process.

In accordance to the present invention it is possible to realize a device in CMOS technology at low cost with the possibility of being integrated with other circuits on the same chip where external circuits are not required. Besides a good equalization with a reduced number of poles and zeros is obtained, in fact with 5 poles and 5 zeros and an
5 equalization band of 260 MHz it is possible to equalize signals transmitted on a line of length of about 350 m.

From the foregoing it will be appreciated that, although specific embodiments of the invention have been described herein for purposes of illustration, various modifications may be made without deviating from the spirit and scope of the
10 invention. Accordingly, the invention is not limited except as by the appended claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
221